



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) EP 0 923 199 A2

(12) EUROPEAN PATENT APPLICATION

(43) Date of publication:
16.06.1999 Bulletin 1999/24

(51) Int. Cl.⁶: H04B 1/707

(21) Application number: 98122538.6

(22) Date of filing: 01.12.1998

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

• Tanaka, Yoshinori
Nakahara-ku, Kawasaki-shi, Kanagawa 211 (JP)
• Kobayakawa, Shuji
Nakahara-ku, Kawasaki-shi, Kanagawa 211 (JP)
• Toda, Takeshi
Nakahara-ku, Kawasaki-shi, Kanagawa 211 (JP)

(30) Priority: 05.12.1997 JP 33536397

(71) Applicant: FUJITSU LIMITED
Kawasaki-shi, Kanagawa 211-8588 (JP)

(74) Representative: HOFFMANN - EITLE
Patent- und Rechtsanwälte
Arabellastrasse 4
81925 München (DE)


(72) Inventors:
• Seki, Hiroyuki
Nakahara-ku, Kawasaki-shi, Kanagawa 211 (JP)

(54) CDMA Interference canceller

(57) An interference canceller includes despread processing parts, a combiner combining interference replica generation signals, a decision part that decides an output signal, spread processing parts coupled to the despread processing parts and the decision part, an attenuation coefficient generator generating an attenua-

tion coefficient dependent on a reliability of the interference replica generation signals, and a multiplier multiplying the output signal of the decision part by the attenuation coefficient.

FIG. 5



EP 0 923 199 A2

Description

BACKGROUND OF THE INVENTION

1. Field of the Invention

[0001] The present invention generally relates to an interference canceller, and more particularly to an interference canceller suitable for a cellular DS/CDMA (Direct Sequence Code Division Multiple Access) mobile communication system or the like.

[0002] In a cellular CD/CDMA mobile communication system, an interference occurs which results from an interference and noise from another mobile station due to correlation between spread codes caused by asynchronism with mobile stations. Such an interference serves as a factor which degrades the channel capacity and the transmission quality of the mobile communication system. Hence, it is desired to precisely eliminate such an interference from a received signal.

2. Description of the Related Art

[0003] Fig. 1 shows a conventional multistage type interference canceller. Each of the stages in the multistage type interference canceller is made up of interference canceller units 81 and a combiner 82. The stages thus configured are cascaded. Fig. 1 shows the multistage type interference canceller having the first stage through the m th stage. Data symbol receivers 83 are provided in the m th stage, which is the final stage.

[0004] The interference canceller units 81 and the final stage are provided in parallel for the respective users' channels. The suffix of the reference number 81 indicating the interference canceller units 81 includes a stage number and a user number corresponding to the user channel (ICU1,1, ICU1,k, ICU2,1, ICU2,k).

[0005] In the first stage, a received signal R_0 is input to the interference canceller units ICU1,1 - ICU1,k corresponding to the users' channels, which output interference replica signals $S_{1,1}$ - $S_{1,k}$ and interference residual signals $d_{1,1}$ - $d_{1,k}$. The combiner 82 combines the interference residual signals $d_{1,1}$ - $d_{1,k}$ corresponding to the users' channels. The combined interference residual signals $d_{1,1}$ - $d_{1,k}$ are subtracted from the received signal R_0 , so that a resultant error signal e_1 of the first stage is obtained.

[0006] In the second stage, the interference canceller units ICU2,1 - ICU2,k are supplied with the error signal e_1 from the combiner 82 of the first stage and the interference replica signals $S_{1,1}$ - $S_{1,k}$ from the interference canceller units ICU1,1 - ICU1,k of the first stage. Then, the interference canceller units ICU2,1 - ICU2,k respectively output interference replica signals $S_{2,1}$ - $S_{2,k}$ and interference residual signals $d_{2,1}$ - $d_{2,k}$. The combiner 82 combines the interference residual signals $d_{2,1}$ - $d_{2,k}$ corresponding to the users' channels. The combined interference residual signals $d_{2,1}$ - $d_{2,k}$ are sub-

tracted from the error signal e_1 of the first stage. Hence, an error signal e_2 of the second stage is obtained.

[0007] In the m th stage, which is the final stage, the receivers ReCm,1 - ReCm,k are supplied with an error signal e_{m-1} and interference replica signals $S_{m-1,1}$ - $S_{m-1,k}$ of the previous stage, and perform an interference eliminating process using the supplied signals, so that data symbols can be decoded. By sequentially repeating the interference eliminating process, the error signal is gradually reduced, and interference replica signals can be obtained from which signals interference between the users can be eliminated.

[0008] Fig. 2 shows a conventional interference Canceller unit, which includes despread processing parts 91, a despreader 91-1, an adder 91-2, a multiplier 91-3, a channel estimation circuit 91-4, a combiner 92, a decision part 93, spread processing parts 94, a multiplier 94-1, an adder 94-2, a respreader 94-3, and a combiner 95.

[0009] The despread processing parts 91 and the spread processing parts 94 are respectively provided to received delayed waves, that is, multipaths. The structure shown in Fig. 2 is configured so as to handle three paths. In Fig. 2, signals corresponding to the respective paths are given a suffix "i" (In Fig. 2, $i = 1 - 3$). The signals corresponding to the paths are referred to RAKE fingers.

[0010] The despread processing part 91 is supplied with the error signal e_{j-1} of the previous stage and the interference replica signals $S_{j-1,1}$ - $S_{j-1,k}$ (these signals of the first stage are zeros). The despreader 91-1 receives the error signal e_{j-1} from the previous stage (the received signal R_0 in the first stage) and performs a despread operation thereon using the spread code. A suffix "j" indicates the stage identification number.

[0011] The adder 91-2 adds the despread signal and the interference replica signals $S_{j-1,2}$ - $S_{j-1,k}$ (which are zeros in the first stage), and creates a resultant receive symbol R_1 of the first path. The channel estimation circuit 91-4 receives the receive symbol R_1 , and estimates channels of paths (the characteristics of transmission paths) using pilot symbols shown in Fig. 3B. Thus, channel estimate values $\hat{\xi}_i$ are obtained for the respective paths.

[0012] The despread signal R_i is multiplied by a complex number $\hat{\xi}_i^*$ of the channel estimate $\hat{\xi}_i$ by the multiplier. Hence, a received symbol can be obtained from which a phase error due to influence of the transmission paths has been eliminated.

[0013] The output signals of the multipliers 91-3 related to the respective paths are diversity-combined (maximal ratio combining) by the combiner 92. A resulting receive symbol $\Sigma R_i \hat{\xi}_i^*$ obtained by the maximal ratio combining is compared with the decision part 93, so that a data symbol can provisionally be decided.

[0014] The signals generated and output by the respread processing parts 91 are called interference replica generation signals. The interference replica gen-

eration signals are converted into interference replica signals and interference residual signals, which are then transferred to the next stage.

[0015] The provisionally decided symbol Zs^* output by the decision part 93 branches into signals corresponding to the paths. In each of the spread processing parts 94, the multiplier 94-1 multiplies the provisionally decided symbol Zs^* by the channel estimation value ξ_i^* . Hence, the provisionally decided data symbol is decomposed into the signals corresponding to the respective paths, which are output to the next stage as interference replica signals $S_{j,1} - S_{j,k}$.

[0016] The adders 94-2 of the spread processing parts 94 respectively add the interference replica signals $S_{j,i} - S_{j,k}$ that are output by the multipliers 94-1 and correspond to the paths and the interference replica signals $S_{j-1,1} - S_{j-1,k}$ supplied from the previous stage. Then, the adders 94-2 respectively output the differences between the interference replica signals $S_{j,i} - S_{j,k}$ of this stage and the interference replica signals $S_{j-1,i} - S_{j-1,k}$. The output signals of the adders 94-2 of the spread processing parts 94 are spread using a spread code in the respective respreaders 94-3. The respread output signals of the respreaders 94-3 corresponding to the respective paths are combined by the combiner 95. The output signals of the combiners 95 of the interference canceller units provided for the respective users' channels are output to the combiner 82 shown in Fig. 1 as interference residual signals $d_{j,1} - d_{j,k}$.

[0017] Fig. 3A shows a conventional final-stage receiver provided in the final stage of the multistage type interference canceller, and Fig. 3B shows a frame format. The final-stage receiver labeled 100 in Fig. 3A includes despread processing parts 101, a combiner 102 and a decoder 103.

[0018] The despread processing parts 101 of the final-stage receiver 100 are supplied with the error signal $em-1$ from the interference replica generation unit of the previous stage and the interference replica signals $Sm-1,1 - Sm-1,k$, and perform the same process as that of the aforementioned despread processing parts 91 of the interference canceller unit. Hence, received symbols can be obtained.

[0019] Each of the despread processing parts 101 of the final-stage receiver 100 is equipped with a despreader 91-1, an adder 91-2, a multiplier 91-3, and a channel estimation circuit 91-4, which are the same as corresponding those of the despread processing part 91 of the interference canceller unit.

[0020] The combiner 102 of the final-stage receiver 100 performs diversity combining (maximal ratio combining) of the received symbols output from the despread processing parts 101. The resultant receive symbol $\Sigma R_i \xi_i^*$ obtained by the maximal ratio combining is compared with a threshold value by the decoder 103. Hence, a data symbol can be reproduced.

[0021] Referring to Fig. 3B, a pilot symbol 104 is interposed between information symbols 105, and is repeat-

edly transmitted by a transmitter so that it is located in a given time position. The pilot signal 104 is predetermined known data symbol, and the receive symbol received can be expressed as $Z \cdot \xi$ where Z denotes a value (complex number) of the pilot symbol 104.

[0022] Since the value of the pilot symbol 104 is known, the channel estimate circuit 91-4 multiplies the receive symbol $Z \cdot \xi$ by the complex conjugate Z^* of the value Z of the pilot symbol, and thus outputs $|Z|^2 \cdot \xi$. Since the magnitude (amplitude) of the pilot symbol is known (may be equal to 1: $|Z| = 1$), an estimate value of the transmission path characteristic ξ of the path. The aforementioned channel estimate circuit 91-4 averages the estimated transmission path characteristics ξ obtained using a plurality of pilot symbols. The average value ξ thus obtained is output as the channel estimate value.

[0023] Fig. 4 shows a receiver of a base station including the interference canceller. A signal received via an antenna (ANT) 110 is input to a radio part (Rx) 120, which then amplifies the received signal by means of an amplifier (LNA) 121. The amplified signal is applied to a band-pass filter (BPF) 122, which eliminates components located outside of a given band. A mixer 123 multiplies the output signal of the band-pass filter 122 by a local oscillation signal from a local oscillator LO. Thus, the received signal is converted into a signal in the base band. High-frequency components contained in the base-band signal are eliminated by a low-pass filter (LPF) 124. The output signal of the low-pass filter 124 is then output to the next stage.

[0024] An A/D converter 130 of the next stage samples the received signal from the radio part 120, and outputs a corresponding digital signal, which is applied to a path search circuit 140. The path search circuit 140 calculates delay times of the respective paths by using a plurality of delay waves received, and outputs delay time information obtained for the respective paths to an interference canceller 150.

[0025] The interference canceller 150 performs despread for the respective paths in the interference replica generation units and the final-stage receivers on the basis of the delay time information obtained for the respective paths. Receive symbols thus obtained are output to decoders 160. Interference between the user channels (spreading codes) and interference between the paths have been eliminated from the receive symbols applied to the decoders.

[0026] Each of the decoders 160 compares the corresponding receive symbol from the interference canceller 150 with a threshold value. Thus, a data symbol can be decoded. Each of the decoders 160 shown in Fig. 4 is the same as the decoder 103 of the final-stage receiver shown in Fig. 3.

[0027] The interference canceller of the above-mentioned type, in which interference is eliminated by subtracting the interference replica signals of the users' channels from the original multiplexed receive signal,

has a disadvantage in that the interference canceling performance greatly depends on the precision of the interference replica signals generated as described above.

[0028] If the interference replica signals having a poor precision are subtracted from the receive signal, interference power may be increased and the receive performance may thus be degraded. The precision of the interference replica signals may be degraded and the interference eliminating capability may be degraded if the signal is received at a relatively low level, or an excessive large number of user channels with respect to the spreading ratio is used or if the transmission paths are quickly varied (under high-speed fading environment).

SUMMARY OF THE INVENTION

[0029] An object of the present invention is to provide an interference canceller in which the above disadvantages are eliminated.

[0030] A more specific object of the present invention is to provide an interference canceller in which interference is eliminated taking into account the receive states of code-multiplexed signals of users' channels so that improved transmission quality can be obtained.

[0031] The above objects of the present invention are achieved by an interference canceller comprising: despread processing parts; a combiner combining interference replica generation signals; a decision part that decides an output signal; spread processing parts coupled to the despread processing parts and the decision part; an attenuation coefficient generator generating an attenuation coefficient dependent on a reliability of the interference replica generation signals; and a multiplier multiplying the output signal of the decision part by the attenuation coefficient.

[0032] The interference canceller may be configured so that the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a position of said interference canceller in a multi-stage formation.

[0033] The interference canceller may be configured so that the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a delay of time of a path through which a signal applied to the interference canceller is propagated.

[0034] The interference canceller may be configured so that the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a number of channels multiplexed.

[0035] The interference canceller may be configured so that the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a level of a signal applied to the interference canceller.

[0036] The interference canceller may be configured so that the attenuation coefficient generator generates

the attenuation coefficient which has a value dependent on a level of a signal received through an antenna branch.

[0037] The interference canceller may be configured so that the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a level of a signal propagated through a path and applied to the interference canceller.

[0038] The interference canceller may be configured so that the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a ratio of signal power to interference/noise power.

[0039] The interference canceller may be configured so that the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on at least two factors indicating a state of receiving a signal.

[0040] The interference canceller may be configured so that the attenuation coefficient generator generates the attenuation coefficient which has a value which is increased as the reliability of the interference replica generation signal is degraded.

[0041] The interference canceller may be configured so that: the interface canceller includes a plurality of stages; and each of the stages includes the despread processing parts, the combiner, the decision part, the spread processing parts, the attenuation coefficient generator and the multiplier.

BRIEF DESCRIPTION OF THE DRAWINGS

[0042] Other objects, features and advantages of the present invention will become more apparent from the following detailed description when read in conjunction with the accompanying drawings, in which:

Fig. 1 is a block diagram of a conventional multi-stage type interference canceller;

Fig. 2 is a block diagram of a conventional interference canceller unit;

Fig. 3A is a block diagram of a conventional final-stage receiver;

Fig. 3B is a diagram of a frame format;

Fig. 4 is a block diagram of a receiver of a base station including an interference canceller;

Fig. 5 is a diagram of an interference canceller unit according to a first embodiment of the present invention;

Fig. 6 is a diagram of an interference canceller unit according to a second embodiment of the present invention;

Fig. 7 is a diagram of an interference canceller unit according to a third embodiment of the present invention;

Fig. 8 is a diagram of an interference canceller unit according to a fourth embodiment of the present invention;

Fig. 9 is a diagram of an interference canceller unit

according to a fifth embodiment of the present invention;

Fig. 10 is a diagram of an interference canceller unit according to a sixth embodiment of the present invention; and

Fig. 11 is a diagram of an interference canceller unit according to a seventh embodiment of the present invention.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0043] Fig. 5 shows an interference canceller unit according to a first embodiment of the present invention. The interference canceller unit shown in Fig. 5 includes despread processing parts 11, a combiner 12, a decision part 13, spread processing parts 14, a combiner 15, an attenuation coefficient generator 16, and a multiplier 17. Each of the despread processing parts 11 includes a desreader 11-1, an adder 11-2, a multiplier 11-3 and a channel estimation circuit 11-4. Each of the spread processing parts 14 includes a multiplier 14-1, an adder 14-2 and a resreader 14-3. The despread processing parts 11 and the spread processing parts 14 are equal in number to received delayed waves, that is, the number of resolvable paths.

[0044] The despread processing parts 11, the combiner 12, the decision part 13, the spread processing parts 14 and the combiner 15 are the same as those of the conventional interference canceller unit shown in Fig. 2, and a description thereof will be omitted.

[0045] The multistage type interference canceller repeatedly performs the interference eliminating process over a plurality of stages. Hence, the precision of the interference replica signals is gradually improved and the interference eliminating performance is thus improved.

[0046] The interference replica signals in the interference canceller unit obtained at an initial stage having a relatively small number of times that the interference eliminating process is repeatedly carried out have a comparatively low precision. As the number of times that the interference eliminating process is repeatedly carried out is increased, the interference replica signals have an improved precision.

[0047] The attenuation coefficient generator 16 is configured as follows taking into account the above. The attenuation coefficient generator 16 generates different values of the attenuation coefficient for different stages of the interference canceller. The values of the attenuation coefficient used at the initial stages function to greatly attenuate the interference replica signals. As the received signal is transferred over an increased number of stages, the attenuation coefficient has values which apply a reduced attenuation to the interference replica signals. That is, when the attenuation coefficient is denoted as α_j (j indicates the stage number), the attenuation coefficient is set so as to have the following val-

ues:

$$0 < \alpha_1 < \alpha_2 < \dots < \alpha_j \dots < \alpha_m < 1.$$

[0048] The attenuation coefficient generator 16 generates the attenuation coefficient having the different values for the different stages of the interference canceller and applies it to the multiplier 17. Then, the multiplier 17 multiplies the interference replica signal output by the decision circuit 13 by the attenuation coefficient. Hence, the interference replica signal is attenuated, in each of the spread processing parts 14, by the attenuation coefficient having the value corresponding to the present stage. Hence, it is possible to suppress the influence of the interference replica signals having a comparatively low precision with respect to the interference eliminating process. The attenuation coefficient is multiplied. Hence, as the attenuation coefficient has a smaller value, the degree of attenuation of the interference replica signal is increased.

[0049] Fig. 6 shows an interference canceller unit according to a second embodiment of the present invention. In Fig. 6, parts that are the same as those shown in Fig. 5 are given the same reference numbers and a repetitive description thereof will be omitted.

[0050] The interference canceller unit shown in Fig. 6 includes a path search circuit 21, an attenuation coefficient generator 22, and a multiplier 23. The path search circuit 21 is the same as the path search circuit 140 in the receiver of the base station equipped with the interference canceller. That is, the path search circuit 21 calculates the delay times for the respective paths from the delayed waves received in multiple formation, and outputs delay time information on the respective paths.

[0051] In a general multi-path environment, a path having a large delay has not only a distance attenuation but also reflection and diffraction that take place a plurality of numbers of times. Hence the signal propagated through such a path and then received has a comparatively low received level. Hence, generally, the interference replica having a comparatively large delay of time has a low reliability.

[0052] With the above in mind, the attenuation coefficient generator 22 shown in Fig. 6 generates the attenuation coefficient having values dependent on the delays of time by referring to the delay time information on the paths output by the path search circuit 21. More particularly, the greater the delay time, the smaller the value of the attenuation coefficient α_i .

[0053] The multiplier 23 multiplies the interference replica generation signal outputs from the multipliers 14-1 of the spread processing parts 14 corresponding to the respective paths (fingers) by the attenuation coefficient. Hence, the levels of the interference replica signals are attenuated based on the delays of time of the respective paths. Hence, it is possible to suppress the interference replica signals having a low reliability with respect to the interference eliminating process.

[0054] Fig. 7 shows an interference canceller unit according to a third embodiment of the present invention. In fig. 7, parts that are the same as those shown in Fig. 5 are given the same reference numbers, and a repetitive description thereof will be omitted.

[0055] The interference canceller unit shown in Fig. 7 includes a base station controller 31, and an attenuation coefficient generator 32. As the number of multiple users' channels is increased, the level of interference between the spreading codes is increased. Thus, the reliability of the reference replicas is degraded. The third embodiment of the present invention is directed to using the different values of the attenuation coefficient dependent on the number of multiple users' channels.

[0056] The base station controller 31 holds information indicating the number of users' channels which are in use for communications. The above information is supplied to the attenuation coefficient generator 32 from the base station controller 31. Then, the attenuation coefficient generator 32 determines the value of the attenuation coefficient based on the number of users' channels which are in use for communications. More particularly, as the number of users' channels is increased, the value of the attenuation coefficient α is reduced.

[0057] The multiplier 33 multiplies the interference replica generation signal output by the decision part 13 by the attenuation coefficient α having the value based on the number of users' channels which are in use for communication. Hence, the level of the interference replica generation signal is attenuated based on the number of users' channels which are in use for communication. Hence, it is possible to suppress the influence of the interference replica signals having a low reliability with respect to the interference eliminating process.

[0058] Fig. 8 shows an interference canceller unit according to a fourth embodiment of the present invention. In Fig. 8, parts that are the same as those of the interference canceller unit according to the first embodiment of the present invention are given the same reference numbers, and a repetitive description thereof will be omitted.

[0059] The interference canceller unit shown in Fig. 8 includes a measurement circuit 41, and an attenuation coefficient generator 42. The measurement circuit 41 measures a signal level or a ratio of signal power to interference/noise power (SIR). The measurement circuit 41 measures the average level of the output signal of the combiner 12 which combines the signal levels obtained after the demodulation by the despread processing parts 11, and outputs the measured average level to the attenuation coefficient generator 42. Then, the attenuation coefficient generator 42 generates the attenuation coefficient having a value dependent on the signal level. More particularly, the lower the signal level, the smaller the value of the attenuation coefficient α .

[0060] The multiplier 43 multiplies the interference replica generation signal output from the decision part

13 by the attenuation coefficient α having the value dependent on the signal level. Thus, the level of the interference replica generation signal is attenuated based on the signal level. It is hence possible to suppress the influence of the interference replica signal having a low reliability with respect to the interference eliminating process.

[0061] The measurement circuit measures the signal level obtained after the demodulation by the despread processing parts 11. Alternatively, the following can be employed. The SIR is obtained from the signal level and the output signal level of the decision part 13. The SIR is applied to the attenuation coefficient generator 42, which outputs the attenuation coefficient based on the received SIR.

[0062] In this case, the lower the SIR, the smaller the attenuation coefficient α . By attenuating the level of the interference replica generation signal on the basis of the SIR, it is possible to suppress the influence of the interference replica signal having a low reliability with respect to the interference eliminating process.

[0063] Fig. 9 shows an interference canceller unit according to a fifth embodiment of the present invention. The unit shown in Fig. 9 includes despread processing parts 51-1 and 51-2, a combiner 52, a decision part 53, spread processing parts 54-1 and 54-2, combiners 55-1 and 55-2, measurement circuits 56-1 and 56-2 that measure the signal level or the SIR, attenuation coefficient generators 57-1 and 57-2, and multipliers 58-1 and 58-2.

[0064] The despread processing parts 51-1 and 51-2 and the spread processing parts 54-1 and 54-2 have the same configurations as those of the despread processing parts 11 and the spread processing parts 14 of the interference canceller unit according to the first embodiment of the present invention.

[0065] Fig. 9 shows a structure of the interference canceller unit used when an antenna diversity is employed. The structure shown in Fig. 9 has two antenna branches 1 and 2. The measurement parts 56-1 and 56-2 are respectively provided to the antenna branches 1 and 2, and measure the signal levels or the SIRs after the demodulation processes by the despread processing parts 51-1 and 51-2 are carried out. The signal levels of the SIRs respectively obtained for the antenna branches 1 and 2 are input to the attenuation coefficient generators 57-1 and 57-2.

[0066] The attenuation coefficient generators 57-1 and 57-2 respectively generate different attenuation coefficients α_1 and α_2 on the basis of the signal levels or the SIRs. More particularly, as the signal levels or the SIRs become lower, the attenuation coefficients α_1 and α_2 are set to smaller values.

[0067] The multipliers 58-1 and 58-2 respectively provided to the antenna branches 1 and 2 multiply the interference replica generation signal output by the decision part 53 by the attenuation coefficients α_1 and α_2 supplied from the attenuation coefficient generators 57-1

and 57-2. Hence, the levels of the interference replica generation signals are attenuated based on the signal levels or the SIRs respectively obtained for the antenna branches 1 and 2. Hence, it is possible to suppress the influence of the interference replica signal having a low reliability with respect to the interference eliminating process.

[0068] Fig. 10 shows an interference canceller unit according to a sixth embodiment of the present invention. In Fig. 10, parts that are the same as those of the interference canceller unit according to the first embodiment of the present invention are given the same reference numbers, and a repetitive description thereof will be omitted.

[0069] The unit shown in Fig. 6 includes a measurement circuit 61 which measures a signal level or an SIR, an attenuation coefficient generator 62, and a multiplier 63. The measurement circuit 61 measures the signal levels or the SIRs obtained after the demodulation processes carried out by the despread processing parts 11 provided to the respective paths (fingers). The measured values obtained for the respective paths are applied to the attenuation coefficient generator 62. Then, the attenuation coefficient generator 62 generates the attenuation coefficients α_i based on the signal levels or the SIRs respectively obtained for the paths (fingers). As the signal levels or the SIRs are lower, the values of the coefficients α_i are smaller.

[0070] The multipliers 63 of the spread processing units 14 multiply the interference replica generation signals from the multipliers 14-1 thereof by the attenuation coefficients α_i having the values based on the signal levels or the SIRs obtained for the respective paths (fingers). Hence, the levels of the interference replica generation signals are attenuated based on the signal levels or the SIRs respectively obtained for the paths (fingers). Hence, it is possible to suppress the influence of the interference replica signal having a low reliability with respect to the interference eliminating process.

[0071] Fig. 11 shows an interference canceller unit according to a seventh embodiment of the present invention. In Fig. 11, parts that are the same as those of the interference canceller unit according to the first embodiment of the present invention are given the same reference numbers, and a repetitive description thereof will be omitted.

[0072] The unit shown in Fig. 11 includes a first attenuation coefficient generator 71 and multipliers 72, and includes a second attenuation coefficient generator 74, a multiplier 75 and a measurement circuit 73 which measures signal levels or SIRs after the demodulation, provided in the respective spread processing parts 14.

[0073] The interference canceller unit according to the seventh embodiment corresponds to a combination of the first-embodiment unit shown in Fig. 5 and the attenuation means employed in the sixth-embodiment unit shown in Fig. 10.

[0074] The first attenuation coefficient generator 71

generates attenuation coefficients α_j for the respective stages. The multiplier 72 multiplies the interference replica generation signal from the decision part 13 by the attenuation coefficient of the present stage generated by the attenuation coefficient generator 71. Hence, it is possible to attenuate the interference replica generation signal having a low reliability.

[0075] The measurement circuit 73 measures the signal levels or the SIRs of the respective paths (fingers) obtained after the demodulation by the despread processing parts 11. The attenuation coefficient generator 74 generates the attenuation coefficients depending on the measured signal levels or SIRs obtained for the respective paths (fingers). The multipliers 75 multiply the interference replica generation signals by the attenuation coefficients depending on the signal levels or the SIRs respectively obtained for the paths. Hence, the level of the interference replica generation signal having a low signal level or SIR can be attenuated for each path (finger).

[0076] Thus it is possible to suppress, in each stage, the influence of the interference replica signal having a low reliability on the basis of the signal levels or the SIRs.

[0077] It is possible to arbitrarily combine the means for attenuating the interference replica signals having a low reliability employed in the first through sixth embodiments of the present invention and to thus improve the reliability of the interference canceller.

[0078] The present invention includes not only the parallel type shown in Fig. 1 in which the multiple users' channels are processed in parallel formation but also other types. For example, the present invention includes a serial type in which the multiple users' channels are processed in serial formation, a single-stage type and a multiple-stage type.

[0079] The present invention also includes a hard-decision (nonlinear) type interference canceller in which a decision on the received symbol is made to obtain an estimate symbol irrespective of the amplitude of the received symbol, and a soft-decision (linear) type interference canceller in which a decision holding the amplitude of the received signal is made.

[0080] As described above, according to the present invention, the interference replica signals generated by the interference canceller unit are controlled using at least one of the attenuation coefficients dependent on the stage, the delays of time of paths, the number of users' channels, the levels of the received signals, and the SIRs. Hence, the degree of attenuation of the interference replica signals having a relatively low reliability is increased (the value of the attenuation coefficient is decreased). Hence, it is possible to optimally eliminate interference on the basis of the receive states of the users' channels which are code-multiplexed and to thus improve the transmission quality.

[0081] The present invention is not limited to the specifically disclosed embodiments, and variations and

modifications may be made without departing from the scope of the present invention.

Claims

1. An interference canceller comprising:

despread processing parts;
a combiner combining interference replica generation signals;
a decision part that decides an output signal;
spread processing parts coupled to the despread processing parts and the decision part;
an attenuation coefficient generator generating an attenuation coefficient dependent on a reliability of the interference replica generation signals; and
a multiplier multiplying the output signal of the decision part by the attenuation coefficient.

2. The interference canceller as claimed in claim 1, wherein the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a position of said interference canceller in a multi stage formation.
3. The interference canceller as claimed in claim 1, wherein the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a delay of time of a path through which a signal applied to the interference canceller is propagated.
4. The interference canceller as claimed in claim 1, wherein the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a number of channels multiplexed.
5. The interference canceller as claimed in claim 1, wherein the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a level of a signal applied to the interference canceller.
6. The interference canceller as claimed in claim 1, wherein the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a level of a signal received through an antenna branch.
7. The interference canceller as claimed in claim 1, wherein the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a level of a signal propagated through a path and applied to the interference canceller.

8. The interference canceller as claimed in claim 1, wherein the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on a ratio of signal power to interference/noise power.

9. The interference canceller as claimed in claim 1, wherein the attenuation coefficient generator generates the attenuation coefficient which has a value dependent on at least two factors indicating a state of receiving a signal.

10. The interference canceller as claimed in claim 1, wherein the attenuation coefficient generator generates the attenuation coefficient which has a value which is increased as the reliability of the interference replica generation signal is improved.

11. The interference canceller as claimed in claim 1, wherein:

the interference canceller includes a plurality of stages; and
each of the stages includes the despread processing parts, the combiner, the decision part, the spread processing parts, the attenuation coefficient generator and the multiplier.

FIG. 1 PRIOR ART




FIG. 2 PRIOR ART




FIG. 3A




FIG. 3B




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10





FIG. 11



(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11)

EP 0 923 199 A3

(12)

EUROPEAN PATENT APPLICATION

(88) Date of publication A3:
14.08.2002 Bulletin 2002/33

(51) Int Cl.7: H04B 1/707

(43) Date of publication A2:
16.06.1999 Bulletin 1999/24

(21) Application number: 98122538.6

(22) Date of filing: 01.12.1998

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

- Tanaka, Yoshinori
Nakahara-ku, Kawasaki-shi, Kanagawa 211 (JP)
- Kobayakawa, Shuji
Nakahara-ku, Kawasaki-shi, Kanagawa 211 (JP)
- Toda, Takeshi
Nakahara-ku, Kawasaki-shi, Kanagawa 211 (JP)

(30) Priority: 05.12.1997 JP 33536397

(71) Applicant: FUJITSU LIMITED
Kawasaki-shi, Kanagawa 211-8588 (JP)

(74) Representative: HOFFMANN - EITLE
Patent- und Rechtsanwälte
Arabellastrasse 4
81925 München (DE)


(72) Inventors:
• Seki, Hiroyuki
Nakahara-ku, Kawasaki-shi, Kanagawa 211 (JP)

(54) CDMA Interference canceller

(57) An interference canceller includes despread processing parts, a combiner combining interference replica generation signals, a decision part that decides an output signal, spread processing parts coupled to the despread processing parts and the decision part, an at-

tenuation coefficient generator generating an attenuation coefficient dependent on a reliability of the interference replica generation signals, and a multiplier multiplying the output signal of the decision part by the attenuation coefficient.

FIG. 5



EP 0 923 199 A3



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 98 12 2538

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
X	US 5 644 592 A (RAPHAELI DAN ET AL) 1 July 1997 (1997-07-01) * abstract; claims 1,6; figure 4 * * column 4, line 55 - column 5, line 27 *	1,2	H04B1/707
Y	* the whole document *	3-11	
X	WO 95 24086 A (THIELECKE JORN ;GRANZOW WOLFGANG (DE); PHILIPS PATENTVERWALTUNG (D) 8 September 1995 (1995-09-08) * page 9, line 16 - page 11, line 7 * * the whole document *	1-4,6	
Y	* abstract; figures 5,6 * * page 3, line 3 - line 21 *	5,7-11	
X	EP 0 776 105 A (NIPPON TELEGRAPH & TELEPHONE) 28 May 1997 (1997-05-28) * abstract; claim 13; figures 15,22 * * column 23, line 41 - column 24, line 19 * * column 28, line 11 - column 31, line 12 *	1,5,7,8	TECHNICAL FIELDS SEARCHED (Int.Cl.6) H04B
Y	* the whole document *	2-4,6,9-11	
X	WO 96 11534 A (NOKIA TELECOMMUNICATIONS OY ;HOTTINEN ARI (FI)) 18 April 1996 (1996-04-18) * abstract; claims 1-3,5-9; figures 2,3 * * page 5, line 2 - page 6, line 3 *	1-11	
P,Y	EP 0 823 796 A (NIPPON ELECTRIC CO) 11 February 1998 (1998-02-11) * abstract; figure 3 * * column 11, line 20 - line 31 * * column 8, line 42 - column 11, line 19 *	2-11	
The present search report has been drawn up for all claims			
Place of search MUNICH		Date of completion of the search 29 April 2002	Examiner Ricciardi, M
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document			

EPO FORM 1503 (03.02) (Rev.01/97)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 98 12 2538

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

29-04-2002

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 5644592	A	01-07-1997	NONE	
WO 9524086	A	08-09-1995	EP 0696398 A1	14-02-1996
			WO 9524086 A2	08-09-1995
			JP 8509592 T	08-10-1996
			US 5719899 A	17-02-1998
EP 0776105	A	28-05-1997	EP 0776105 A1	28-05-1997
			KR 212306 B1	02-08-1999
			US 6137788 A	24-10-2000
			CA 2197342 A1	27-12-1996
			CN 1158193 A ,B	27-08-1997
			WO 9642146 A1	27-12-1996
			JP 2855173 B2	10-02-1999
WO 9611534	A	18-04-1996	FI 944739 A	08-04-1996
			AU 695984 B2	27-08-1998
			AU 3654995 A	02-05-1996
			CN 1159870 A	17-09-1997
			EP 0784888 A2	23-07-1997
			WO 9611534 A2	18-04-1996
			JP 11511915 T	12-10-1999
			NO 971543 A	05-06-1997
EP 0823796	A	11-02-1998	JP 2798128 B2	17-09-1998
			JP 10051353 A	20-02-1998
			EP 0823796 A2	11-02-1998
			KR 251332 B1	15-04-2000
			US 6081516 A	27-06-2000

EPO FORM P0459

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82

THIS PAGE BLANK (USPTO)